

TITLE

SOLID STATE IMAGE PICKUP APPARATUS

[0001] This application is a divisional application of Application No. 09/040,275, filed March 18, 1998, which is a divisional application of Application No. 08/705,002, filed August 29, 1996, now U.S. Patent No. 5,771,070, issued on June 23, 1998, which is a continuation application of Application No. 08/237,046, filed July 15, 1994 (now abandoned), which is a continuation application of Application No. 07/547,996, filed June 13, 1990, now U.S. Patent No. 5,331,421, issued on July 19, 1994, which is a continuation-in-part application of (1) Application No. 07/314,275, filed February 23, 1989 (now abandoned), which is a continuation application of Application No. 06/929,892, filed November 13, 1986 (now abandoned); and (2) Application No. 07/460,012, filed January 2, 1990 (now abandoned), which is a continuation application of Application No. 07/096,534, filed September 14, 1987, now U.S. Patent No. 4,914,519, issued on April 3, 1990.

BACKGROUND OF THE INVENTION

Field of the Invention

[0002] The present invention relates to a solid state image pickup apparatus and, more particularly, to a solid state image pickup apparatus having a plurality of photoelectric transducer elements each having a capacitor electrode on a control electrode region of a corresponding semiconductor transistor.

[0003] The present invention also relates to a solid state image pickup apparatus for selectively reading out a plurality of sensor signals and, more particularly, to a solid state image pickup apparatus capable of eliminating unnecessary components such as variations in dark signals and drive noise.

Related Background Art

[0004] A TV or SV camera with an image sensor such as a CCD or MOS sensor has an aperture mechanism. Photoelectric transducer apparatuses each having a TV or SV camera with an automatic aperture mechanism are described in Japanese Patent Disclosure (Kokai) Nos. 12759/1985 to 12765/1985.

[0005] This photoelectric transducer apparatus includes a photosensor having a plurality of sensor cells each having a capacitor formed on a control electrode of a corresponding semiconductor transistor.

[0006] In the conventional photoelectric transducer apparatus described above, noise is often mixed in an output signal read out from the photosensor cells due to variations in dark voltage generated in the cells within an arbitrary store time.

[0007] An output signal corresponding to the dark current component generated within the photosensor cell is prestored as reference optical information in an external memory in a conventional apparatus. A reference output signal derived from the reference optical information and an output signal from the actual optical information read out from the photosensor cell are compared with each other, and the output signal of the actual optical information is corrected, thereby eliminating the noise component caused by the dark voltage.

[0008] In the conventional photoelectric transducer apparatus described above, in order to constitute a photoelectric transducer system, the resultant system is undesirably complicated since a separate external circuit including a noise removal memory is required.

[0009] When a conventional photoelectric transducer apparatus is applied to a video camera or the like, the following problem occurs. When photoelectric transducer cells are arranged in a two-dimensional matrix and scanned in the vertical and horizontal directions, holes are stored in the base of each photoelectric transducer cell in a store mode upon reception of strong light. The base potential is forward-biased with respect to the emitter potential. The potential of a vertical line connected to the emitter electrode of each photoelectric transducer cell receiving strong light is increased to cause a blooming phenomenon. In order to prevent this, it is proposed that the vertical lines are grounded for a period excluding the readout operation, thereby refreshing the charge overflowing onto the vertical line. However, the vertical line can be grounded

for only the horizontal blanking period, i.e., about 10 μ s. Therefore, the charge overflowing onto the vertical line during the horizontal scanning period still causes the blooming phenomenon.

[0010] In the readout mode, when image signals are sequentially output by horizontal scanning after they are stored in a vertical line, a dummy signal is generated during the storage of the signal in the vertical line. In other words, a smear phenomenon occurs.

[0011] In addition, the period for performing the refresh operation in the conventional apparatus is about 10 μ s in the horizontal blanking period. The refresh time is short and results in incomplete refreshing and hence an after image phenomenon.

[0012] Furthermore, assume that when the conventional photoelectric transducer apparatus is used as a single-plate type solid-state imaging device in a color television video camera, color filters are deposited or adhered onto the pixels. If an alignment scheme such as a Bayer alignment is used to form vertical lines in units of colors, i.e., R, G, and B, at least two vertical lines are required for the pixels of each column. In this case, since the vertical line portion does not serve as the photosensitive portion, the light-receiving area is reduced by the two vertical lines for each column. In other words, the opening of the aperture is undesirably reduced.

[0013] In a conventional photosensitive transducer apparatus, negative and positive voltages are required to bias an output amplifier, and the constitution is thus complicated. It is difficult to read out the signal component without degrading the frequency characteristics.

[0014] Fig. 15A is a schematic circuit diagram of a conventional solid-state image pickup apparatus.

[0015] Referring to Fig 15A, signals from sensors S1 to Sn are respectively amplified by amplifiers A1 and An, and transistors T1 to Tn are sequentially turned on. A dot sequential output appears on an output line 101A. The dot sequential signal is amplified by a buffer amplifier 102A, and the resultant signal appears as an output signal Vout.

[0016] In the conventional image pickup apparatus described above, variations in input/output characteristics of the amplifiers A1 to An are included in the sensor signals as the dot sequential output appearing on the output line 101A. As a result, steady pattern noise undesirably occurs.

[0017] Fig. 15B shows a schematic arrangement of another conventional photoelectric transducer apparatus.

[0018] Referring to Fig 15B, signals read out from photosensors S1 to Sn are temporarily stored in storage capacitors C1 to Cn. Transistors T1 to Tn are sequentially turned on at timings of a scanning circuit SH, and the readout signals sequentially appear on an output line 101A and are output to an external device through an amplifier 102A.

[0019] In the above photoelectric transducer apparatus, however, unnecessary components such as dark signals and drive noise of the photosensors are undesirably included.

[0020] Drive noise is defined as noise generated when a photosensor is driven to read out a signal. The drive noise components are noise caused by manufacturing variations such as element shapes and smear caused by element-isolation and depending on radiation amounts.

[0021] The dark signal is defined as a dark current of a photosensor and greatly depends on accumulation time and temperature of the photosensor.

[0022] This drive noise will be described in detail. Variations in drive capacity of a drive element for driving a photoelectric transducer element and variations in capacity of a photoelectric transducer element cause variations in a leakage component of drive pulses. These variation components as an information signal are superposed on a necessary photoelectric transducer signal and are read out. The cause of generation of drive noise will be described below.

[0023] Fig. 15C is a schematic view of a photoelectric transducer element described in Japanese Patent Laid-Open Gazette No 12764/1985, Fig. 15D is a timing chart of drive pulses for driving the photoelectric transducer element shown in Fig. 15C, and Fig. 15E is a chart showing the base potential of the photoelectric transducer element.

[0024] Referring to Fig 15C, the photoelectric transducer element includes a base accumulation type bipolar transistor B, a drive capacitor C_{ox} for reverse- or forward-biasing the transistor B in response to a drive pulse ϕ_r , and a refresh transistor Q_r . The transistor B has junction capacitances C_{bc} and C_{be} . It should be noted that C_{ox} , C_{bc} , and C_{be} are referred to as capacitances or capacitors hereinafter, as needed. The capacitances C_{ox} , C_{bc} , and C_{be} are added to obtain a charge storage capacitance C_{tot} .

[0025] The operation of the photoelectric transducer element will be described below.

[0026] Assume that the initial value of a base potential V_B is given as V_0 . When the drive pulse ϕ_r is set at a potential V_{ϕ_r} at time t_1 , a voltage V_a is applied to the base of the transistor B through the drive capacitor C_{ox} . In this case, the voltage V_a can be represented as follows:

$$\begin{aligned}
V_a &= C_{ox}/(C_{ox} + C_{bc} + C_{be}) \times V\phi_r \\
&= (C_{ox}/C_{tot}) \times V\phi_r \quad \dots \quad (1)
\end{aligned}$$

[0027] When the drive pulse ϕ_{rh} is set at a high potential at time t_2 , a transistor Q_r is turned on.

[0028] When the transistor B is forward-biased, the base potential V_B is abruptly decreased. A time interval T_C between time t_2 and time t_3 is a so-called refresh time interval.

[0029] The drive pulse ϕ_r is set at zero at time t_3 , and a voltage $-V_a$ is added to the base voltage V_B , so that the base voltage V_B is set at V_2 . This reverse-biased state is the accumulation state.

[0030] The above description was confined to one photoelectric transducer element. However, a line or area sensor has a large number of photoelectric transducer elements. The capacitances of the capacitors C_{ox} , C_{bc} , and C_{be} between a large number of photoelectric transducer elements vary by a few fractions of 1%. For example, if the following conditions are given:

[0031] $C_{ox} = C_{bc} = C_{be} = 0.014$ pF, and $V\phi_r = 5$ V and the capacitance variation is 0.2 %, then a variation ΔV_a in capacitance division voltage V_a is about 3 mV.

[0032] The variation ΔV_a can be reduced by refreshing. However, when the refresh mode is changed to an accumulation operation mode (time t_3), the variation occurs again to produce ΔV_b . The variation ΔV_b does not satisfy the relation $\Delta V_b = -\Delta V_a$, and the correlation cannot be established therebetween according to test results.

[0033] The above fact is assumed to be derived from different bias voltage dependencies of C_{bc} and C_{be} .

[0034] In the next read cycle, when the transistor B is forward-biased, the variation in base potential thereof is approximated as follows:

$$\Delta V^2 = \Delta V_a^2 + \Delta V_b^2 + 2K\Delta V_a\Delta b \quad \dots \quad (2)$$

for K equal to -1 or more. As a result, the variation ΔV becomes steady drive noise of about 4 to 5 mV.

[0035] The variation in leakage component of such a drive pulse (to be referred to as drive noise hereinafter) is eliminated according to the following conventional technique. That is, the above drive noise is stored in a memory means and is read out and subtracted from the signal read out from the sensor to obtain a true information signal.

[0036] The conventional drive noise correction technique described above causes a bulky, expensive photoelectric transducer element which does not have any industrial advantage.

[0037] In particular, in case the numbers of elements arranged in the horizontal direction and vertical direction are five hundred respectively, an area sensor requires 250,000 photoelectric elements arranged in a matrix form. In addition, when the resolution of the sensor is also taken into consideration, a memory of several megabits is required.

[0038] The unnecessary signals such as drive noise and a dark signal pose serious problems when an image of a dark object is to be picked up, i.e., image pickup at a low intensity. In the low-intensity image pickup mode, an information signal level is low and accordingly the S/N ratio is degraded. As a result, image quality is degraded. In order to improve image quality, the unnecessary signals must be reduced.

[0039] As described above, however, the dark signal primarily depends on temperature and charge accumulation time, although the drive noise rarely depends thereon. If these unnecessary signals are to be eliminated, the dark signal must be separated from the drive noise and a correction coefficient must be determined, thus requiring a large-capacity memory. As a result, signal processing is complicated and expensive, and an image pickup apparatus is undesirably bulky.

SUMMARY OF THE INVENTION

[0040] It is an object of the present invention to provide a photoelectric transducer apparatus capable of solving the conventional drawbacks described above.

[0041] It is another object of the present invention to provide a simple photoelectric transducer apparatus capable of eliminating variations in dark voltage.

[0042] It is still another object of the present invention to provide a photoelectric transducer apparatus comprising optical information storing means for storing optical information (light or bright signals) read out from a photoelectric transducer element and dark voltage storing means for storing a voltage corresponding to a dark voltage component read out from the photoelectric transducer element, wherein actual optical information stored in the optical information storing means is simultaneously read out together with the dark voltage component stored in the dark voltage storing means onto separate output lines, thereby correcting the information corresponding to the dark voltage in units of optical sensor cells and hence removing noise caused by variations in dark voltage from the output signal from the photosensor cells.

[0043] In order to achieve the above object, according to an aspect of the present invention, there is provided a photoelectric transducer apparatus having a plurality of photoelectric transducer elements each having a capacitor electrode formed on a control electrode of a corresponding semiconductor transistor, the apparatus being adapted to sequentially select each element in units of lines, to control a potential of the control electrode of the selected photoelectric transducer element through the capacitor electrode, to store carriers in the control electrode region, and to read out a signal component corresponding to the amount of charge stored in the control electrode region, comprising: optical information storing means for storing optical information read out from the photoelectric transducer element; and dark voltage storing means for storing a voltage corresponding to a dark voltage read out from the photoelectric transducer element, wherein actual optical information stored in the optical information storing means and information corresponding to the dark voltage component stored in the dark voltage storing means are simultaneously read out onto different information output lines.

[0044] The information corresponding to the dark voltage component stored in the dark voltage storing means is read out onto the information output line therefor, and at the same time the information corresponding to the dark voltage is corrected in units of photosensor cells, thereby eliminating noise caused by variations in dark voltage.

[0045] The noise corresponding to the dark voltage component can, therefore, be processed within the sensor. An external circuit or the like need not be used to easily constitute a system configuration, thereby obtaining a low-cost photoelectric transducer apparatus.

[0046] It is still another object of the present invention to provide an imaging element and an apparatus using the same, wherein the after image, blooming, and smearing can be prevented with a simple construction.

[0047] It is still another object of the present invention to provide a color imaging element having a large aperture.

[0048] In order to achieve these objects, according to another aspect of the present invention, there is provided a photoelectric transducer apparatus comprising:

- a plurality of photoelectric transducer cells;

- a signal read line for reading out signals from the plurality of photoelectric transducer elements; and

- a plurality of capacitors for selectively storing the signals read out through the signal read line.

[0049] According to this aspect of the present invention, since the plurality of capacitors for selectively storing the signals read out through the signal read line are provided, the image signal appearing on the vertical line can be shortened, thereby reducing the frequency of occurrence of the blooming and smearing phenomena. Since the capacitor can be disconnected from the pixel after the image signal is stored in the capacitor, the refresh time can be prolonged to reduce the occurrence of the after image phenomenon. In addition, if the photoelectric transducer apparatus is used in a color video camera, the number of capacitors can be that of the color signals of the row pixels, and only one vertical line is used, thereby increasing the aperture.

[0050] It is still another object of the present invention to provide a photoelectric transducer apparatus wherein a single power source can be used without degrading the signal component of the read signal.

[0051] In order to achieve the above object, according to still another aspect of the present invention, there is provided a photoelectric transducer apparatus for reading output a read signal from a photoelectric transducer element through an amplifier after the read signal is temporarily stored in a storing means, comprising switching means for properly applying a bias voltage to the storing means.

[0052] With the above arrangement, the reference potential of the store capacitor can be properly changed to use a single power source without degrading the signal component of the read signal.

[0053] It is still another object of the present invention to provide a photoelectric transducer apparatus little subjected to smearing or blooming.

[0054] In order to achieve the above object, according to still another aspect of the present invention, a capacitor is arranged in a vertical signal line through a switch to store the signal from the photoelectric transducer cell in the capacitor, thereby resetting the vertical signal line, so that the signal component in the capacitor is free from smearing or blooming.

[0055] It is another object of the present invention to eliminate variations in drive noise in units of sensor cells.

[0056] It is still another object of the present invention to compensate for variations in electrical characteristics of a plurality of amplifiers arranged for sensor cells.

[0057] In order to achieve the above objects according to an aspect of the present invention, there is provided a solid state image pickup apparatus having a selector for selecting a plurality of sensor signals through corresponding amplifiers, comprising a processing circuit for calculating a difference between a selected sensor signal and a reference signal selected through the same circuit for selecting the sensor signal.

[0058] The sensor signal selected by the selector, therefore, includes a noise component caused by variations in amplifier characteristics since the sensor signal is amplified by the corresponding amplifier. For this reason, the reference signal is selected through the same amplifier which has amplified the sensor signal, so that the amplifier noise is superposed on the reference signal. A difference between the selected sensor signal and the selected reference signal is calculated to eliminate the noise component.

[0059] According to another aspect of the present invention, there is provided a photoelectric transducer apparatus having storage means for storing a signal from a photoelectric transducer element, wherein the storage means comprises first storage means for storing the signal read out from the photoelectric transducer element and second storage means for storing a residual signal after the photoelectric transducer element is refreshed, and further comprising difference processing means for calculating a difference between the readout and residual signals respectively stored in the first and second storage means.

[0060] Since the residual signal obtained upon completion of refreshing is subtracted from the readout signal, the unnecessary components such as a dark signal level and drive noise of the photoelectric transducer element can be eliminated.

[0061] A MOS, electrostatic induction, or base accumulation type photosensor may be used as a photoelectric transducer element.

[0062] "Refreshing" of the photoelectric transducer element means erasure of optical information of the photoelectric transducer element. In some photosensors, optical information is erased simultaneously when the information is read out. However, in some photosensors, optical information is kept unerased even after the information is read out.

[0063] According to still another aspect of the present invention, in order to eliminate the conventional drawbacks described above, there is provided a solid state image pickup apparatus comprising a plurality of photoelectric transducer elements, first storage means, arranged in units of photoelectric transducer elements, for storing a video signal, second storage means, arranged in units of photoelectric transducer elements, for storing noise components, first readout means for simultaneously and independently reading out signals for photoelectric transducer elements of a plurality of horizontal lines from the first storage means, and second readout means for adding signals for the photoelectric transducer elements of the plurality of horizontal lines from the second storage means and for reading out a sum signal.

[0064] With the above arrangement, it is assumed that the drive noise is generated as a sum of noise components generated in the refresh, charge accumulation, and readout modes of the photoelectric transducer element and the drive noise level is substantially identical in each mode. A difference between the photoelectric transducer signal read out upon completion of exposure and drive noise read out in the photoelectric transducer signal readout mode is calculated to eliminate the drive noise. It should be noted that the noise components are read out after they are added, thereby reducing the number of read lines.

[0065] According to still another aspect of the present invention, in order to eliminate the conventional drawbacks described above, there is provided a solid state image pickup apparatus comprising photoelectric transducer elements, a plurality of storage capacitors for storing readout signals when the photoelectric transducer elements are read-accessed a plurality of times, dot sequential processing means for converting signals from the storage capacitors into a dot sequential signal, and clamping means for

clamping some components of the dot sequential signal from the dot sequential processing means.

[0066] With the above arrangement, it is assumed that the drive noise is generated as a sum of noise components generated in the refresh, charge accumulation, and readout modes of the photoelectric transducer element and the drive noise level is substantially identical in each mode. The photoelectric transducer signal read out upon completion of exposure and drive noise read out in the photoelectric transducer signal readout mode are converted into a dot sequential signal, and the drive noise component is clamped, thereby eliminating the drive noise included in the photoelectric transducer signal components.

[0067] The above and other objects, features, and advantages of the present invention will be apparent from the following detailed description in conjunction with the accompanying drawings.

BRIEF DESCRIPTION OF THE DRAWINGS

[0068] Fig. 1 is a circuit diagram of a photoelectric transducer apparatus according to a first embodiment of the present invention;

[0069] Fig. 2 is a timing chart for explaining the operation of the apparatus in Fig. 1;

[0070] Fig. 3A is a circuit diagram of a photoelectric transducer apparatus according to a second embodiment of the present invention;

[0071] Fig. 3B is a circuit diagram showing the main part of a third embodiment;

[0072] Fig. 4 is a timing chart for explaining the operation of the second and third embodiments of the present invention;

[0073] Fig. 5 is a circuit diagram of a photoelectric transducer apparatus according to a fourth embodiment of the present invention;

[0074] Fig. 6 is a timing chart for explaining the operation of the apparatus in Fig. 5;

[0075] Fig. 7 is a circuit diagram of a photoelectric transducer apparatus according to a fifth embodiment of the present invention;

[0076] Fig. 8 is a timing chart for explaining the operation of the apparatus in Fig. 7;

[0077] Fig. 9 is a circuit diagram of a photoelectric transducer apparatus according to a sixth embodiment of the present invention;

[0078] Fig. 10 is a circuit diagram of a photoelectric transducer apparatus according to a seventh embodiment of the present invention;

[0079] Fig. 11 is a timing chart for explaining the apparatus in Fig. 10;

[0080] Fig. 12A is a circuit diagram for explaining a basic operation of the seventh embodiment of the present invention;

[0081] Fig. 12B is a timing chart showing the voltage waveforms in the seventh embodiment;

[0082] Fig. 13 is a block diagram of an imaging device on the basis of the above embodiments of the present invention;

[0083] Fig. 14 is a circuit diagram showing part of an eighth embodiment of the present invention;

[0084] Fig. 15A is a schematic circuit diagram of a conventional solid state image pickup apparatus;

[0085] Fig. 15B is a schematic view of another conventional solid state image pickup apparatus;

[0086] Figs. 15C to 15E are views for explaining the principle of generation of drive noise of a photoelectric transducer element;

[0087] Figs. 16A and 16B are schematic circuit diagrams showing a solid state image pickup apparatus according to an embodiment of the present invention;

[0088] Fig. 17 is a circuit diagram showing an arrangement of switches SW1 to SWn in the apparatus of Fig. 16A;

[0089] Fig. 18 is a circuit diagram showing another arrangement of switches SW1 to SWn in the apparatus of Fig. 16A;

[0090] Fig. 19A is a circuit diagram showing another arrangement of a difference processing circuit in the apparatus of Fig. 16A;

[0091] Fig. 19B is a timing chart for explaining the operation of the difference processing circuit shown in Fig. 19A;

[0092] Fig. 20A is a schematic circuit diagram showing a solid state image pickup apparatus according to another embodiment of the present invention;

[0093] Fig. 20B is a timing chart for explaining the operation of the apparatus shown in Fig. 20A;

[0094] Fig. 21 is a block diagram showing an image pickup system using the apparatus (of any embodiment of Figs. 15-20 described above) as an image pickup device;

[0095] Fig. 22A is a schematic sectional view of a photoelectric transducer cell described in Japanese Patent Laid-Open Gazettes Nos. 12759/1985 to 12765/1985;

[0096] Fig. 22B is an equivalent circuit diagram thereof;

[0097] Fig. 23 is a graph showing the relationship between a width t of a refresh pulse applied to the photoelectric transducer cell and a photoelectric transducer cell output after refreshing;

[0098] Fig. 24 is a circuit diagram for explaining a basic arrangement of a solid state image pickup apparatus according to still another embodiment of the present invention;

[0099] Fig. 25 is a timing chart for explaining the operation of the apparatus shown in Fig. 24;

[0100] Fig. 26 is a circuit diagram showing the overall arrangement of the apparatus shown in Fig. 24;

[0101] Figs. 27A and 27B are timing charts for explaining two operation modes of the apparatus shown in Fig. 24;

[0102] Fig. 28 is a circuit diagram of a solid state image pickup apparatus according to still another embodiment of the present invention;

[0103] Fig. 29 is a detailed circuit diagram of a readout circuit Ri in the apparatus shown in Fig. 28;

[0104] Fig. 30 is a timing chart for explaining the operation of the apparatus shown in Fig. 28;

[0105] Fig. 31 is a block diagram showing an image pickup system using the apparatus (Fig. 24) as an image pickup device;

[0106] Fig. 32 is a circuit diagram showing an image pickup apparatus according to still another embodiment of the present invention;

[0107] Fig. 33 is a block diagram showing an image pickup system using the image pickup apparatus (Fig. 32) as an area sensor;

[0108] Fig. 34 is a circuit diagram of a solid state image pickup apparatus according to still another embodiment of the present invention;

[0109] Fig. 35 is a timing chart for explaining the operation of the apparatus shown in Fig. 34;

[0110] Fig. 36 is a schematic view showing an arrangement when the apparatus in Fig. 34 is applied to an area sensor; and

[0111] Fig. 37 is a timing chart for explaining the operation of the area sensor shown in Fig. 36.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

[0112] Fig. 1 is a circuit diagram of a photoelectric transducer apparatus as a line sensor according to a first embodiment of the present invention, and Fig. 2 is a timing chart for explaining the operation thereof.

[0113] Referring to Figs. 1 and 2, capacitor electrodes 101 of photosensor cells 100 are commonly connected to a driving line, and collector electrodes 102 thereof are commonly connected to a positive voltage terminal.

[0114] A driving terminal is connected to the driving line.

[0115] A pulse signal is applied to the driving terminal to drive the photosensor cells 100. Emitter terminals 103 of the photosensor cells 100 are connected to vertical signal lines and commonly connected to each other through reset FETs 104. The emitter terminals 103 are connected to a ground terminal GND.

[0116] The gate electrodes of the FETs 104 are commonly connected to a first reset terminal.

[0117] The FETs 104 are switching field effect transistors.

[0118] The vertical signal lines are connected to store capacitors 106 through FETs 105 and to the source electrodes of FETs 107. The drain electrodes of the FETs 107 are

commonly connected to a horizontal signal line. The gate electrodes of the FETs 105 are commonly connected to a control terminal.

[0119] The gate electrodes of the FETs 107 are respectively connected to output terminals of a scanning circuit 108.

[0120] Horizontal signal lines are connected to an external output terminal through an output amplifier 109 and to the ground terminal GND through an FET 110.

[0121] The gate terminal of the FET 110 is connected to a second reset terminal.

[0122] The FET 110 is a field effect transistor for resetting the horizontal line.

[0123] The operation of the circuit in Fig. 1 will be described with reference to a timing chart in Fig. 2.

[0124] The control and first reset terminals are simultaneously set at H level during the reset time. During the reset time, the optical information stored in the store capacitors 106 is discharged through the FETs 104.

[0125] When the control terminal is set at H level and the first reset terminal is set at L level, the optical information stored in the photosensor cells 100 is read out onto the vertical signal lines by applying the readout pulse signal to the driving terminal.

Therefore, the optical information is stored in the store capacitors 106.

[0126] In this manner, when the readout pulse signal is set at H level, readout operation of the photosensor cells 100 is started. After the lapse of a predetermined period of time, the readout pulse signal is set at L level, thereby terminating the readout operation.

[0127] When the control terminal is set at L level, and the first reset and driving terminals are set at H level, the refresh operation state is obtained. The optical information stored in the photosensor cells 100 is erased through the FETs 104.

[0128] When the refresh pulse signal is set at L level, the refresh operation is ended.

[0129] Thereafter, during the period until the readout operation state is obtained again, the store time for storing the carriers in the photosensor cells 100 is defined.

[0130] The signal pulses from the output terminals of the scanning circuit 108 are used to sequentially turn on the FETs 107 according to the shift timings.

[0131] The optical information signals stored in the store capacitors 106 are sequentially read out onto the horizontal lines by horizontal scanning of the scanning circuit 108. The readout signals are amplified by the output amplifier 109 and appear at the external output terminal.

[0132] When all optical information signals stored in the store capacitors 106 are read out completely, the reset time is initialized again.

[0133] The above operations are thus repeated.

[0134] With the above arrangement, the signal charge is not kept on the vertical signal line for a long period of time, thus reducing blooming and smearing.

[0135] A second embodiment of the present invention will be described with reference to the accompanying drawings.

[0136] Fig. 3A is a circuit diagram of a photoelectric transducer apparatus according to the second embodiment.

[0137] Referring to Fig. 3A, photosensor cells 1 as the photoelectric transducer elements are one-dimensionally arranged.

[0138] Capacitor electrodes 2 of the photosensor cells 1 are commonly connected to a driving line and to a driving terminal. Collector electrodes 3 of the photosensor cells 1 are commonly connected to a positive voltage terminal.

[0139] Emitter electrodes 4 of the photosensor cells 1 are respectively connected to vertical lines 5. The vertical lines 5 are commonly connected through FETs 6. The FETs 6 are connected to a ground terminal 7.

[0140] The gate electrodes of the FETs 6 are commonly connected to a first reset terminal.

[0141] The capacitors 9 and the source electrodes of the FETs 10 are respectively connected to the vertical lines 5 through FETs 8. The capacitors 9 are connected to a ground terminal 12 through a ground line 11.

[0142] The capacitors 9 are signal charge store capacitors, respectively.

[0143] The gate electrodes of the FETs 10 are respectively connected to output terminals 14 of the scanning circuit 13. The drain electrodes of the FETs 10 are connected to an output amplifier 16 through a horizontal line 15. The output terminal of the output amplifier 16 is connected to an external output terminal 17, so that an output voltage is extracted from the external output terminal 17.

[0144] The gate electrodes of the FETs 10 are respectively connected to the gate electrodes of FETs 18. The drain electrodes of the FETs 18 are connected to an output amplifier 20 through an output line 19.

[0145] The output terminal of the output amplifier 20 is connected to an external output terminal 21, so that an output voltage is extracted from the external output terminal 21.

[0146] The source electrodes of the FETs 18 are connected to the vertical lines 5 through FETs 22.

[0147] In the above embodiment, one electrode of each of capacitors 24 is connected between a corresponding one of the source electrodes of the FETs 18 and a

corresponding one of the FETs 22 through a corresponding one of vertical lines 23.

The other electrode of each of the capacitors 24 is connected to the ground line 11.

[0148] The capacitors 24 serve as dark voltage store capacitors, respectively. Reset FETs 26 are connected between the lines 15 and 19 and ground, respectively. The gate electrodes of the FETs 26 are connected to the second reset terminal. A control circuit 27 supplies timing pulses (Fig. 4) to the respective terminals.

[0149] The operation of the above embodiment will be described below.

[0150] As shown in the timing chart of Fig. 4, the photosensor cells store optical information corresponding to the amounts of light received in a light store operation during the light irradiation store time.

[0151] During a predetermined period of time until the light information readout, the photosensor cells 1 perform store operations of carriers upon light irradiation. During the reset time, both the control and first reset terminals are set at H level, so that the charges stored in the capacitors 9 are reset through the corresponding FETs 6.

[0152] The control terminal is set at H level, and the first reset terminal is set at L level. When a readout pulse voltage is applied to the driving terminal, the optical or light information stored in the photosensor cells 1 is read out onto the vertical lines, and the light information is stored in the capacitors 9.

[0153] When the light information readout time has elapsed, the first reset terminal is set at H level and the control terminal is set at L level. In this state, when the refresh pulse voltage is applied to the driving terminal, the photosensor cells 1 are maintained in the refresh state. The light information stored in the photosensor cells 1 is erased through the FETs 6.

[0154] When the refresh time has elapsed, the photosensor cells 1 are temporarily shielded from light so that a shading time is started.

[0155] In this case, the photosensor cells 1 store the dark voltage generated in the dark state. It should be noted that the dark voltage store time is controlled to be equal to the light irradiation store time.

[0156] Subsequently, both the dark voltage readout terminal and the first reset terminal are set at H level to reset through the FETs 6 the charges stored in the capacitors 24 during the reset time.

[0157] The light information corresponding to the dark voltage components stored in the photosensor cells 1 is read out onto the vertical lines under the following conditions. The dark voltage readout terminal is set at H level, the first reset terminal is set at L level, and the readout pulse voltage E_r is applied to the driving terminal. Therefore, the dark voltage signals are stored in the corresponding capacitors 24.

[0158] When the dark voltage readout time has elapsed, the dark voltage readout terminal is set at L level, and the first reset terminal is set at H level. The refresh pulse voltage E_0 is applied to the driving terminal to set the photosensor cells 1 in the refresh state.

[0159] When a predetermined period of time has elapsed, the refresh pulse voltage applied to the driving terminal is set at L level. Therefore, the refresh time is terminated. Along with this, the shading time is ended, and the first reset terminal is set at L level.

[0160] Subsequently, clocks are supplied to the scanning circuit 13 to sequentially shift the output pulses from the output terminals 14 thereof. The FETs 10 and 18 are sequentially turned on in response to these timing pulses.

[0161] By this horizontal scanning, light information signals are sequentially read out from the capacitors 9 onto the horizontal line 15. In synchronism with the readout operation, the information signals corresponding to the dark voltage components stored in the capacitors 24 are read out onto the output line 19.

[0162] In this manner, the light information signals read out onto the horizontal line 15 are output to the external output terminal 17 through the output amplifier 16. The information signals corresponding to the dark voltage components read out onto the output line 19 are output to the external output terminal 21 through the output amplifier 20, so that the output voltage is thus extracted from this external output terminal.

[0163] For example, the readout operation for one horizontal scanning time is completed, and the reset time is started. Thereafter, the above operations will be repeated.

[0164] Since the photoelectric transducer apparatus of this embodiment is operated as described above, an additional external circuit which was required in the conventional photoelectric transducer apparatus to remove the noise component caused by the dark voltage need not be used, thereby simplifying the system configuration. Therefore, demand for a low-cost photoelectric transducer apparatus can be satisfied.

[0165] In the above embodiment, the actual light information signals simultaneously read out onto the corresponding lines and the information signals corresponding to the dark voltage components are amplified by the output amplifiers 16 and 20 in an output circuit 25, and the amplified signals are extracted through the external output terminals, respectively. However, the present invention is not limited to the above arrangement. As shown in Fig. 3B, (a third embodiment), the output circuit 25 may be replaced with a differential amplifier 28 to subtract the information corresponding to the dark voltage

components from the actual light information. Light information representing a difference may be output from a terminal 29.

[0166] In the second and third embodiments, the dark voltage store time is set to be equal to the light irradiation time. However, such setting need not be performed.

[0167] For example, by effectively utilizing the relationship between the dark voltage store time and the amount of dark voltage components generated by the photosensor cells 1, i.e., a substantially proportional relationship, the dark voltage store time may be set to be shorter than the light irradiation time, and gains of the output amplifiers 16 and 20 in the output circuit 25 may be independently controlled. Alternatively, the capacitances of the store capacitors 9 and 24 are adjusted to obtain the same effect as in the above embodiments.

[0168] In the second and third embodiments, the photosensor cells are one-dimensionally aligned. However, the arrangement of the cells is not limited to this.

[0169] As described above, the photoelectric transducer apparatus comprises light information storing means for storing light information read out from the photoelectric transducer element, and dark voltage storing means for storing a voltage corresponding to the dark voltage component read out from the photoelectric transducer element. The actual light information stored in the light information storing means and the information corresponding to the dark voltage component stored in the dark voltage storing means are simultaneously read out from the separate output lines. Therefore, the information corresponding to the dark voltage included in the output can be corrected in units of photosensor cells when the actual optical information read out from the photosensor cell is output, and noise caused by variations in dark voltage can be removed from the output signal. Unlike in the conventional photoelectric transducer

apparatus, an additional external circuit is not required to simplify the system configuration. In addition, demand for an economical photoelectric transducer apparatus can be satisfied.

[0170] A fourth embodiment of the present invention will be described in detail with reference to the accompanying drawings.

[0171] Fig. 5 is a circuit diagram of photoelectric transduces elements arranged in a 4 x 4 matrix to constitute a photoelectric transducer apparatus.

[0172] The photoelectric transducer apparatus includes: basic photosensor cells 100 (the collector of each bipolar transistor is connected to the substrate and the substrate electrode), horizontal lines 31, 31', 31" and 31''' serving as the readout-refresh pulse lines; a vertical shift register 32 for generating a readout pulse; buffer MOS transistors 33, 33', 33", and 33''' arranged between the vertical shift register 32 and the horizontal lines 31, 31', 31", 31'''; a terminal 34 for applying a pulse ϕ_R to the drains of the buffer MOS transistors 33, 33', 33", and 33'''; a vertical shift register 32' for generating a refresh pulse; buffer MOS transistors, 47, 47', 47", and 47''' formed between the vertical shift register 32' and the horizontal lines 31, 31', 31", and 31'''; a terminal 48 for applying a pulse ϕ_F to the drains of the buffer MOS transistors 47, 47', 47", and 47'''; vertical lines 35, 35', 35", and 35''' serving as vertical readout lines for reading out signal charges from the basic photosensor cells 100; capacitors 37-1, 37-2, 37-1', 37-2', 37-1", 37-2", 37-1"', and 37-2''' for storing these signal charges; transfer MOS transistors 36-1, 36-2, 36-1', 36-2', 36-1", 36-2", 36-1"', and 36-2''' arranged between the vertical lines 35, 35', 35", and 35''' and the capacitors 37-1, 37-2, 37-1', 37-2', 37-1", 37-2", 37-1"', and 37-2'''; a horizontal shift register 46 for generating a pulse for selecting each store capacitor; gate MOS transistors 38-1, 38-2, 38-1', 38-2', 38-1", 38-2", 38-1"', and 38-2''' for charging/discharging the store capacitors 37-1, 37-2, 37-1', 37-

2', 37-1", 37-2", 37-1'", and 37-2'"; output lines 39-1 and 39-2 for reading out the store voltages and supplying them to an amplifier; MOS transistors 40-1 and 40-2 for refreshing the charges on the readout lines; a terminal 41 for applying the refresh pulse to the MOS transistors 40-1 and 40-2; transistors 42-1 and 42-2 such as bipolar transistors, MOSFETs or JFETs for amplifying the output signals; output terminal 43-1 and 43-2 of the transistors 42-1 and 42-2; MOS transistors 44, 44', 44", and 44'" for refreshing the charges stored on the vertical lines 35, 35', 35", and 35'"; a terminal 45 for supplying a pulse to the gates of the MOS transistors 44, 44', 44", and 44'"; a horizontal shift register 46 for turning on the MOS transistors 38-1, 38-2, 38-1', 38-2', 38-1", 38-2", 38-1'", and 38-2'"; and a control circuit 200 for supplying signals to the respective terminals.

[0173] The operation of the photoelectric transducer apparatus will be described with reference to Fig. 5 and a timing chart of Fig. 6.

[0174] Assume that the collector potential of the photosensor cells is kept at a positive potential in the following description.

[0175] The store operation is performed until time t_1 , and holes corresponding to the amounts of light incident on the photoelectric transducer cells 100 are respectively stored in their p-type base regions.

[0176] At time t_1 , a pulse signal ϕ_{vc} rises to turn on the transistors 44, 44', 44", and 44'". A pulse signal ϕ_{T1} rises to turn on the transistors 36-1, 36-1', 36-1", and 36-1'" to refresh the store capacitors 37-1, 37-1', 37-1", and 37-1'". A pulse signal ϕ_{Hc} rises to turn on the transistors 40-1 and 40-2 to refresh the residual charges on the output lines 39-1 and 39-2. Subsequently, the pulse signal ϕ_{vc} falls to turn off the transistors 44, 44', 44", and 44'". and the vertical lines 35, 35', 35", and 35'". and the capacitors 37-1,

37-1', 37-1'', and 37-1''' are set in the floating state. A pulse signal ϕ_{v1} is output from the vertical shift register 32 to turn on the transistor 33. When a readout pulse signal ϕ_R is then applied to the terminal 34 and the horizontal line 31 through the transistor 33, the readout operation of the photoelectric transducer cells 100 of the first row is started. By this readout operation, the readout signals from the cells of the first row appear on the vertical lines 35, 35', 35'', and 35''' and in the store capacitors 37-1, 37-1', 37-1'', and 37-1'''. When the readout operation is completed, the pulse signal ϕ_{T1} falls to turn off the transistors 36-1, 36-1', 36-1'', and 36-1'''. The capacitors 37-1, 37-1', 37-1'', and 37-1''' and the vertical lines 35, 35', 35'', and 35''' are disconnected, and then the residual charges on the vertical lines 35, 35', 35'', and 35''' are refreshed.

[0177] At time t_2 , a pulse signal ϕ_{T2} rises to turn on the transistors 36-2, 36-2', 36-2'', and 36-2''' so that the charges in the store capacitors 37-2, 37-2', 37-2'', and 37-2''' are refreshed. Subsequently, the pulse signal ϕ_{vc} falls to turn off the transistors 44, 44', 44'', and 44'''. A pulse signal ϕ_{v2} is output from the vertical shift register 33', and the readout pulse signal ϕ_R is supplied to the horizontal line 31' through the terminal 34. In this state, the readout operation of the photoelectric transducer cells 100 of the second row is started. By this readout operation, the readout signals from the cells 100 of the second row appear on the vertical lines 35, 35', 35'' and 35''' and in the store capacitors 37-2, 37-2', 37-2'', and 37-2'''. Upon completion of the readout operation for the second row, the pulse signal ϕ_{T2} falls to turn off the transistors 36-2, 36-2', 36-2'' and 36-2''', and the capacitors 37-2, 37-2', 37-2'', and 37-2''' and the lines 35, 35', 35'', and 35''' are disconnected. The pulse signal ϕ_{vc} rises to refresh the residual charges from the vertical lines 35, 35', 35'' and 35'''.

[0178] At time t_3 , the pulse signal ϕ_{Hc} falls to turn off the transistors 40-1 and 40-2. The pulse signal ϕ_{H1} is output from the horizontal shift register 46 to turn on the

transistors 38-1 and 38-2. The charges in the capacitors 37-1 and 37-2 are amplified by the transistors 42-1 and 42-2 through the transistors 38-1 and 38-2 and the output lines 39-1 and 39-2. The amplified signals appear at the terminals 43-1 and 43-2. When this output operation is completed, the pulse signal ϕ_{Hc} rises to refresh the output lines 39-1 and 39-2. Subsequently, the pulse signals ϕ_{H2} and ϕ_{H3} are sequentially output from the horizontal shift register 46. In the same manner as described above, the readout signals from the cell of the first row and the second column and the cell of the second row and the second column and the readout signals from the cell of the first row and the third column and the cell of the second row and the third column are sequentially output from the terminals 43-1 and 43-2. Every time the readout signals appear, the output lines 39-1 and 39-2 are refreshed.

[0179] At time t_4 , a pulse signal ϕ_{cl} is output from the vertical shift register 32' to turn on the transistors 47 and 47'. A pulse signal ϕ_F is applied to the terminal 48 so that the refresh pulse is applied to the horizontal lines 31 and 31' through the transistors 31 and 31'. As a result, the refresh operation of the photoelectric transducer cells 100 of the first and second rows is performed.

[0180] The readout and refresh operation for the cells 100 of the third and fourth rows are performed at time t_5 in the same manner as in the cells of the first and second rows. The readout and refresh operations are repeated for the cells 100 of the first and second rows at time t_6 . The above operations are repeated.

[0181] In the above operation, the time required for sending the readout signal onto the vertical line is the period between rising of the pulse signal ϕ_R and falling of the pulse signal ϕ_{T1} , i.e., between the times t_1 and t_2 when the output from the photoelectric transducer cell 100 of the first row and the first column is assumed. This time interval apparently has a large margin. In the conventional photoelectric transducer apparatus

applied in the video camera, the vertical line selected last by horizontal scanning stores the signal charge for about 52.5 μ s. For example, if the time interval between rising of the pulse signal ϕ_R and falling of the pulse signal ϕ_{T1} is set to be 0.5 μ s, the apparatus of this embodiment can be improved by about 105 times (40 dB) for blooming and smearing, as compared with the conventional apparatus.

[0182] Since the store capacitors are arranged, the photosensitive transducer cells are disconnected from the store capacitors by turning off the transistors 36-1, 36-2, 36-1', 36-2', 36-1'', 36-2'', 36-1''', and 36-2''' after the signal charges are stored in the store capacitors, the photoelectric transducer cells 100 can be sufficiently refreshed. For example, the refresh time may be a time interval between times t_3 and t_5 , i.e., one horizontal scanning cycle. Therefore, the after image phenomenon can be reduced as compared with the conventional case.

[0183] If the photoelectric transducer apparatus is applied to a color video camera and color filters are formed on the sensor cells, the number of capacitors is that of the colors of column cells, and the operation as described above is performed. In this case, only one vertical line is used for each column, and the aperture of the sensor cells is not reduced. For example, as shown in Fig. 5, the color filters R, G, and B are arranged according to the Bayer's scheme, and the cells are operated at the timings shown in Fig. 6. B signals are stored in the capacitors 37-1 and 37-1'', G signals are stored in the capacitors 37-2, 37-1', 37-2'', and 37-1''', and R signals are stored in the capacitors 37-2' and 37-2''', respectively.

[0184] In the above embodiment, the two vertical lines are simultaneously accessed. However, the number of lines is not limited to two, but can be extended to three or more. In this case, the number of store capacitors is that of vertical pixels which are simultaneously accessed.

[0185] Fig. 7 is a circuit diagram showing a fifth embodiment of the present invention.

A decoder 49 is arranged between a vertical shift register 32 and horizontal lines 31, 31', 31'', and 31''', and a control circuit 200 is operated at timings shown in Fig. 8.

[0186] In this embodiment, the decoder 49 also serves the function of the photoelectric transducer cell refresh vertical register 46 of the fourth embodiment (Fig. 5), thereby further simplifying the system configuration.

[0187] The operation of the fifth embodiment will be described with reference to the timing chart of Fig. 8. Assume that the store operation is performed until time t_1 , and that the holes corresponding to the amounts of light incident on the photoelectric transducer cells 100 are respectively stored in their p-type base regions.

[0188] At time t_1 , a pulse signal ϕ_{vc} has already risen, the vertical lines have already been grounded, and a pulse signal ϕ_{T1} rises to refresh the charges of the capacitors 37-1, 37-1', 37-1'', and 37-1'''. Thereafter, when the pulse signal ϕ_{vc} falls to set the vertical lines and the capacitors in the floating state, the decoder 49 outputs a pulse ϕ_{D1} .

[0189] The signals from the photoelectric transducer cells 100 of the first row appear on the vertical lines and in the capacitors 37-1, 37-1', 37-1'', and 37-1'''. After the readout operation is completed, the pulse signal ϕ_{T1} falls to disconnect the capacitors 37-1, 37-1', 37-1'', and 37-1''' from the vertical lines, and the pulse signal ϕ_{vc} rises again to refresh the vertical lines. The pulse signal ϕ_{T2} rises to refresh the capacitors 37-2, 37-2', 37-2'', and 37-2''', and the pulse signal ϕ_{vc} then falls. When the pulse signal ϕ_{D2} rises again, the signals from the photoelectric transducer cells of the second row appear on the vertical lines and the capacitors 37-2, 37-2', 37-2'', and 37-2'''. Thereafter, the pulse signal ϕ_{T2} falls and the pulse signal ϕ_{vc} rises to refresh the

vertical lines. In this state, the signals from the first row are stored in the capacitors 37-1, 37-1', 37-1'', and 37-1''', and the signals from the second row are stored in the capacitors 37-2, 37-2', 37-2'', and 37-2'''.

[0190] In the same manner as in the first embodiment, these stored signals are sequentially read out from time t_3 to time t_5 . In this case, during the time interval from time t_4 to a time immediately before time t_5 , the pulse signals $\phi D1$ and $\phi D2$ are set at high level, so that the photoelectric transducer cells 100 of the first and second rows are refreshed.

[0191] The readout and refresh operations of the photoelectric transducer cells of the third and fourth rows are performed in the same manner as described above.

[0192] According to this embodiment, the refresh and readout operations of the photoelectric transducer cells of each cell are performed by using a single vertical shift register, thereby simplifying the system configuration.

[0193] In the above embodiment, the two output lines are used. However, the number of output lines may be three or more. For example, as shown in a sixth embodiment of Fig. 9, four output lines are used in units of colors of filters. In this case, the load of the output lines can be reduced to 1/2 of that of the two output lines. In addition, an image processing circuit can also be simplified.

[0194] The arrangement of Fig. 9 is different from that of Fig. 5 in the following points. Output lines 39-3 and 39-4 are added. Transistors 38-1 and 38-1''' are connected to a transistor 39-3 instead of the transistor 39-1. Transistors 38-2' and 38-2''' are connected to a transistor 39-4 instead of the transistor 39-2. Transistors 40-3 and 40-4, the gates of which are commonly connected to the gates of transistors 40-1 and 40-2, are added to refresh the output lines 39-3 and 39-4. A transistor 42-3 for outputting a signal from

the output signal 39-3, an output terminal 43-4, a transistor 42-4 for outputting a signal from the output line 39-4, and an output terminal 43-4 are added.

[0195] Other arrangements of Fig. 9 are the same as those of Fig. 5, and the same reference numerals as in Fig. 5 denote the same parts in Fig. 9.

[0196] In the photoelectric transducer apparatuses in the fourth to sixth embodiments as described above in detail, a plurality of capacitors are arranged for each readout line of the photoelectric transducer cells. The signal charges can be stored in the capacitors in a short period of time, and then the readout lines can be disconnected therefrom.

Therefore, blooming and smearing caused by the presence of the signal charges on the readout lines can be completely prevented.

[0197] Furthermore, since the refresh time can be sufficiently prolonged, the after image phenomenon can be effectively prevented.

[0198] Many lines are often simultaneously accessed when the photoelectric transducer apparatus is applied to a color video camera or the like. The capacitors corresponding to the pixels to be accessed are arranged for each readout line. The number of readout lines need not be increased, and thus the aperture can be increased.

[0199] A seventh embodiment of the present invention will be described below.

[0200] Fig. 10 is a circuit diagram of a photoelectric transducer apparatus according to the seventh embodiment of the present invention.

[0201] Referring to Fig. 10, a driving pulse ϕ_R is applied from a control circuit 200 to capacitor electrodes of photoelectric transducer cells S1 to Sn. A predetermined positive voltage is applied to the collector electrodes of the cells S1 to Sn. The emitter electrodes of the cells S1 to Sn are respectively connected to vertical lines VL1 to VLn. Each of these vertical lines is connected to one terminal of a corresponding one of store

capacitors C1 to Cn (each having a capacitance Ct) through a corresponding one of transistors Qt1 to Qtn. The other terminal of each of the capacitors C1 to Cn properly receives a bias voltage Vct in a manner to be described later.

[0202] One terminal of each of the capacitors C1 to Cn is connected to an output line 201 through a corresponding one of transistors QS1 and QSn. The output line 201 has a stray capacitance Ch equal to the capacitance Ct of each of the store capacitors C1 to Cn.

[0203] The input terminal of an output amplifier 202 is connected to the output line 201 and to a transistor Qrh for properly applying a reset voltage Vrh. The value of the reset voltage Vrh is selected within the range wherein the linearity of the output amplifier 202 is not degraded. In this embodiment, the range is 1.5 to 3.5 V. The output amplifier 202 is connected to a single power source and is driven thereby.

[0204] Pulses ϕ_{h1} to ϕ_{hn} are sequentially applied from a scanning circuit 103 to the gate electrodes of the transistors QS1 and QSn. A pulse ϕ_t is applied to the gate electrodes of the transistors Qt1 to Qtn.

[0205] A voltage Vvc is applied to the respective vertical lines through transistors Qr1 to Qrn. The gate electrodes of these transistors receive a pulse ϕ_{vc} . A control circuit 200 supplies a driving pulse to each terminal. Fig. 11 is a timing chart for explaining the operation of the control circuit.

[0206] The transistors Qr1 to Qrn and the transistors Qt1 to Qtn are turned on in response to the pulses ϕ_{vc} and ϕ_t , respectively, to clear (duration T1) the capacitors C1 to Cn. Subsequently, the pulse ϕ_{vc} is set at L level, and the capacitors C1 to Cn are charged (duration T2) with the readout signals from the photoelectric transducer cells in

response to the driving pulse ϕ_r . In this case, the bias voltage V_{ct} is the ground potential.

[0207] After the bias voltage V_{ct} is set to be +2V, the signals from the capacitors C_1 to C_n are output at timings of the shift pulse ϕ_{h1} to ϕ_{hn} .

[0208] More specifically, the transistor QS_1 is turned on in response to the pulse ϕ_{h1} . As described above, the signal read out from the photoelectric transducer cell S_1 and stored in the capacitor C_1 is read out onto the output line 201. Subsequently, the transistor Q_{rh} is turned on in response to the pulse ϕ_{rh} , and the output line 201 is reset to the reset voltage V_{rh} (e.g., +2V). In the same manner as described above, the readout signals stored in the capacitors C_2 to C_n are sequentially read out onto the output line 101 and are output through the output amplifier 102 (a duration T_3).

[0209] When the output operation is completed, the refresh operation is performed in response to the pulse ϕ_{vc} and the driving pulse ϕ_r (a duration T_4).

[0210] The basic operation of the circuit in Fig. 10 will be described below.

[0211] Fig. 12 A is a circuit diagram for explaining the basic operation of the circuit in Fig. 10, and Fig. 12 B is a timing chart showing the voltage waveforms.

[0212] Referring to Fig. 12 A, a switch for selecting the ground voltage (contact A) or the bias voltage of +2V (contact B) is equivalently connected to the store capacitor C_t . A switch Q_{rh} for applying the reset voltage V_{rh} (+2V) is equivalently connected to the output line 201. Also assume that the voltage of the capacitor C_t is v_1 , and that the voltage of the output line 201 is v_2 .

[0213] The capacitor C_t is connected to the contact A and grounded, and the readout signal from the sensor is stored in the capacitor C_t . The capacitor C_t is then connected to the contact B and receives the bias voltage of +2V. The voltage of the capacitor C_t

at the time of zero level of the readout signal is set to be equal to the reset voltage of the output line.

[0214] Subsequently, when the switch Q_s is closed, the $1/2$ component of the signal of the voltage v_l appears on the output line 201 since $C_t = C_h$. This voltage is input as a voltage V_2 to the output amplifier 202. Closing of the switch Q_{rh} causes resetting of the output line 201 at the voltage of $+2V$ (Fig. 12 B).

[0215] According to this embodiment, only the signal component is input to the output amplifier 202, and the input voltage does not greatly vary upon resetting. The dynamic range of the output amplifier 202 can therefore be increased. The amplitude of the voltage V_{rh} or V_{ct} can have a large margin.

[0216] By setting the potential of the output line 201 connected to the input terminal of the output amplifier 202 at a low potential excluding the ground potential, the V_{ss} terminal of the output amplifier 202 can be grounded and a positive voltage ($+5V$ in this case) can be applied to the V_{dd} terminal thereof by a single power source. (For example, if the reset potential is zero, the negative and positive potentials are respectively applied to the V_{ss} and V_{dd} terminals, and thus two power sources are required).

[0217] If the bias voltage of the capacitor C_t is not changed, the potential of the output line 201 greatly varies between the reset potential V_{rh} and the signal component potential of the readout signal. The sensor signal is normally amplified to a proper signal level by a signal processor (to be described later). If the above unnecessary component is generated, the circuit system is saturated since the unnecessary component has a magnitude larger than that of the signal component, thereby degrading the signal component. However, according to the above embodiment, the above

problem does not occur. If an output amplifier having a wide dynamic range is arranged, it prevents use of a low-level driving source and design of a compact imaging device. However, according this embodiment, the wide dynamic range of the amplifies 202 is not required, so that a compact imaging device can be provided.

[0218] Now consider the charge/discharge time. A reset potential portion of the output signal V_{out} can sufficiently drive a load capacitance (a bonding capacitance, a wiring capacitance, an input transistor capacitance, and the like) by a source current of a source follower circuit. However, the signal component portion of the output signal becomes a sink current of the source follower circuit. If an output resistance is not sufficiently small, a discharge time constant is increased to degrade linearity of a small signal. A decrease in output resistance causes current consumption loss. According to this embodiment, since the dynamic range of the output amplifier can be narrowed, this problem does not occur.

[0219] In order to eliminate the unnecessary voltage variation component, a sample/hold (S/H) circuit is required. The relationship between a timing pulse for the S/H circuit and the signal component is very important. It is desirable not to arrange the S/H circuit to obtain good temperature characteristics and the power source voltage characteristics. However, if the S/H circuit is not arranged, the blocking characteristic curve of a low-pass filter becomes steep when the output signal is band-limited thereby, and hence image quality is degraded. However, according to this embodiment, since the S/H circuit need not be used, the apparatus of this embodiment can be stably operated against temperature and voltage variations

[0220] Fig. 13 shows a schematic arrangement of an imaging device using the above embodiment.

[0221] Referring to Fig. 13, an imaging element 501 has the same arrangement as in the embodiment of Fig. 10. An output signal V_{out} from the imaging element 501 is gain-controlled by a signal processing circuit 502 and is output as a standard NTSC signal or the like.

[0222] Various pulses ϕ and the bias voltage V_{ct} for driving the imaging element 501 are generated by a control circuit 200. The control circuit 200 is operated under the control of the control unit 504. In this case, the control circuit 200 also serves as the switching means for properly applying the bias voltage V_{ct} . The control unit 504 controls the gain or the like of the signal processing circuit 502 on the basis of the output from the imaging element 501 to control the amount of light incident on the imaging element 501.

[0223] The bias voltage V_{ct} applied to the store capacitors $C1$ to Cn is supplied from the control circuit 200. However, an internal power source 601 shown in Fig. 14, may be arranged. In this case, the internal power source 601 is operated in response to a control pulse ϕ_{ct} from the control unit 504 to generate the bias voltage V_{ct} .

[0224] In the photoelectric transducer apparatus as described in detail, a simple method of temporarily changing the reference potential of the capacitors in the readout mode is employed, so that only a single power source for the imaging driving voltage can be used. As a result, the imaging device can be made more compact at lower power consumption.

[0225] Fig. 16A is a schematic circuit diagram of a solid state image pickup apparatus according to an embodiment of the present invention.

[0226] Referring to Fig. 16A, switches $SW1$ to SWn are arranged to select corresponding inputs in response to pulses ϕ_{c1} to ϕ_{cn} . The switches $SW1$ to SWn

respectively receive sensor signals S1 to Sn from photosensors S1 to Sn arranged in a line or a matrix form. The switches SW1 to SWn also receive signals E from reference signal sources E, respectively.

[0227] The output terminals of the switches SW1 to SWn are respectively connected to the input terminals of amplifiers A1 to An. The output terminals of the amplifiers A1 to An are connected to an output line 101A through corresponding transistors T1 to Tn. Pulses ϕ_1 to ϕ_n from a scanning circuit SH such as a shift register are respectively supplied to the gate electrodes of the transistors T1 to Tn. The transistors T1 to Tn are turned on in response to the pulses ϕ_1 to ϕ_n .

[0228] The output line 101A is grounded through a transistor 103A. A pulse ϕ_{hrs} is applied to the gate electrode of the transistor 103A. The output line 101A is also connected to a difference processing circuit 1A. An output signal Vout free from noise components is output from the difference processing circuit 1A.

[0229] In the difference processing circuit 1A in this embodiment, the output line 101A is connected to an amplifier 11A. The input terminals of sample/hold (S/H) circuits 12A and 13A are connected to the output terminal of the amplifier 11A. Pulses ϕ_{h1} and ϕ_{h2} as control signals are respectively supplied to the S/H circuits 12A and 13A so that the S/H circuits 12A and 13A hold the inputs at the input timings of these pulses, respectively. The output terminals of the S/H circuit 12A and 13A are respectively connected to the noninverting and inverting input terminals of a differential amplifier 14A. The output signal Vout is output from the differential amplifier 14A.

[0230] The operation of this embodiment will be described below.

[0231] When the reference signal E is input to the amplifier A1 upon operation of the switch SW1, the reference signal E is amplified by the amplifier A1, and an amplified

signal $E1'$ is output to the transistor T1. In this case, only the transistor T1 is kept on in response to the pulse ϕ_1 , and other transistors T2 to Tn are kept off. The reference signal $E1'$ is selected by the transistor T1 and appears on the output line 101A. The reference signal $E1'$ is held in the S/H circuit 12A through the amplifier 11A. More specifically, the pulse ϕ_{h1} is supplied to the S/H circuit 12A when it holds the reference signal $E1'$.

[0232] The reference signal $E1'$ held by the S/H circuit 12A is a signal reflecting variation characteristics of the amplifiers A1, i.e., a signal including a noise component N1 which becomes a steady pattern noise. In other words, $E1' = E + N1$.

[0233] Subsequently, the transistor 103A is turned on in response to the pulse ϕ_{hrs} to remove the charge left on the output line 101A. An output signal from the sensor S1 is input to the amplifier A1 through the switch SW1. In the same manner as described above, a sensor signal $S1'$ amplified by the amplifier A1 appears on the output line 101A through the ON transistor T1 and is held by the S/H circuit 13A through the amplifier 11A.

[0234] The sensor signal $S1'$ held by the S/H circuit 13A also reflects variation characteristics, i.e., a signal including the noise component N1 ($S1' = S1 + N1$).

[0235] When the reference signal $E1'$ and the sensor signal $S1'$ are respectively held by the S/H circuits 12A and 13A, the signals $S1'$ and $E1'$ are input to the differential amplifier 14A. The output V_{out} from the differential amplifier 14A is a difference ($S1' - E1'$) between the sensor and reference signals $S1'$ and $E1'$, thereby obtaining a signal ($S1 - E$) free from the noise component N1. In this case, the reference signal E represents the reference level of the sensor signal S1, so that $E = 0$ is established.

Therefore, the output signal V_{out} is the sensor signal $S1$ before being subjected to the influence of the amplifier $A1$.

[0236] When the sensor signal $S1$ is output in this manner, the residual charge on the output line 101A is eliminated by the transistor 103A. At the timings in the same manner as described above, the sensor signals $S2$ to S_n free from the noise components $N2$ to N_n are sequentially output from the differential amplifier 14A.

[0237] In the above description, the reference signal E is read out prior to the corresponding sensor signal. However, each sensor signal may be read out prior to the reference signal E .

[0238] In the above description, the reference and sensor signals $E1'$ and $S1'$ are held in the separate S/H circuits, respectively. However, one of the S/H circuits may be omitted, and the output terminal of the amplifier 11A may be directly connected to the amplifier 14A (Fig. 16B). In this case, one readout signal is held by the S/H circuit 12A in response to the pulse ϕ_{h1} , and the output signal V_{out} is output from the differential amplifier 14A at the read timing of the other readout signal.

[0239] Fig. 17 is a circuit diagram showing an arrangement of switches $SW1$ to SW_n in the apparatus shown in Fig. 16A.

[0240] Referring to Fig. 17, a transistor 201A is turned on in response to a pulse ϕ_t to store the sensor signal $S1$ in a capacitor $C1$. Subsequently, a transistor 203A is turned on in response to a pulse ϕ_{cb} to output the reference signal E to the amplifier $A1$.

[0241] When the reference signal $E1'$ is held as described above, the transistor 202A is turned on in response to a pulse ϕ_{ca} to output the sensor signal $S1$ from the capacitor $C1$ to the amplifier $A1$.

[0242] The switches SW2 to SWn have the same arrangement as that of the switch SW1, and operations of the switches SW2 to SWn are also the same as that of the switch SW1.

[0243] Fig. 18 is a circuit diagram showing another arrangement of the switches SW1 to SWn in the apparatus of Fig. 16A.

[0244] In this arrangement, the reference signal E is generated by drive noise caused by variations in leakage component of the sensor.

[0245] Referring to Fig. 18, a transistor 301A is turned on in response to a pulse $\phi t1$ to store the sensor signal S1 in a capacitor C11. Subsequently, a transistor 303A is turned on in response to a pulse $\phi t2$. A sensor signal representing absence of optical information or the dark state thereof serves as the reference signal E. This reference signal E is stored in a capacitor C12. In this state, a drive noise component of the corresponding sensor is stored in the capacitor C12. In the same manner as described above, a transistor 304A is turned on to output the reference signal E from the capacitor C12 to an amplifier A1 and then a transistor 302A is turned on to output the sensor signal S1 from the capacitor C11 to the amplifier A1.

[0246] By using the sensor drive noise component as the reference signal E, the output $V_{out} (= S1' - E1')$ from the differential amplifier 14A is free from the sensor drive noise component as well as the noise component N1 of the amplifier A1.

[0247] Fig. 19A is a circuit diagram showing another arrangement of the difference processing the circuit in the apparatus shown in Fig. 16A, and Fig. 19B is a timing chart for explaining the operation thereof.

[0248] Difference processing is performed by a clamping circuit in this arrangement.

[0249] Referring to Figs. 19A and 19B, the reference signal E1' amplified by the amplifier A1 appears on the output line 101A and is input to a clamp circuit through an amplifier comprising transistors 15A and 16A. In this case, the claim circuit comprises a capacitor 17A and a transistor 18A. Since the transistor 18A in the clamp circuit is kept on in response to a clamp pulse ϕ_s , the level of the reference signal E1' is clamped as the reference level. As a result, the sensor signal S1' subsequently appearing on the output line 101A is amplified by an amplifier of transistors 19A and 20A using the reference signal E1' as a reference level. In the same manner as in Fig. 15, the output signal Vout obtained by removing the reference signal E1' from the sensor signal S1' is obtained. Similarly, the clamp pulse ϕ_s is generated at a read timing of the reference signal E1', and the sensor signals S1 to Sn free from the noise components are sequentially output.

[0250] Fig. 20A is a schematic circuit diagram of a solid state image pickup apparatus according to another embodiment of the present invention, and Fig. 20B is a timing chart for explaining the operation thereof.

[0251] Referring to Fig. 20A, sensors B1 to Bn (to be referred to as B hereinafter) are base accumulation type phototransistors. A base potential of each transistor is controlled through a capacitor, and the carriers excited upon incidence of light are accumulated in the base region of the transistor. The accumulated voltage is read out as a sensor signal, or the accumulated carriers are removed.

[0252] A read or refresh pulse ϕ_r is applied to the capacitor electrodes of the sensors B. The emitter electrodes of the sensors B which are adapted to read out sensor signals S1 to Sn (to be referred to as S hereinafter) are grounded through transistors Qr1 to Qrn (to be referred to as Qr hereinafter), respectively. The emitter electrodes are connected to

temporary storage capacitors C11 to Cn1 through transistors Qa1 to Qan (to be referred to as Qa hereinafter) and to temporary storage capacitors C12 to Cn2 through transistors Qc1 to Qcn (to be referred to as Qc hereinafter), respectively.

[0253] The capacitors C11 to Cn1 are connected to the gate electrodes of amplifiers A1 to An through transistors Qb1 to Qbn, respectively. The capacitors C12 to Cn2 are connected to the gate electrodes of the amplifiers A1 to An through transistors Qd1 to Qdn, respectively.

[0254] A voltage Vcc is applied to the first terminals of the amplifiers A1 to An, and an output line 501A is commonly connected to the second input terminals thereof.

[0255] A pulse $\phi a1$ is applied to the gate electrodes of the transistors Qb1 to Qbn through transistors Qe1 to Qen. A pulse $\phi b1$ is applied to the gate electrodes of the transistors Qd1 to Qdn through transistors Qf1 to Qfn.

[0256] Pulses $\phi 1$ to ϕn from a scanning circuit SH are sequentially supplied to the gate electrodes of the transistors Qe1 to Qen, Qf1 to Qfn, and T1 to Tn, respectively.

[0257] A transistor 502A is connected to the output line 501A, and a voltage Vss is applied to the output line 501A through the transistor 502A. A signal S' amplified by each amplifier and appearing on the output line 501A is input to the difference processing circuit 1A, and difference processing as described above is performed. It should be noted that the difference processing circuit 1A in this embodiment is of a differential type using the S/H circuit shown in Fig. 16A.

[0258] The operation of the apparatus of this embodiment will be described with reference to Fig. 20B.

[0259] Assume that carriers corresponding to the intensity levels of the incident light are stored in the base regions of the sensors B, respectively.

[0260] For a time interval T_{m1} , the transistors Q_r are kept on in response to the pulse ϕ_{rh} , and the emitter electrodes of the sensors B and the vertical lines are grounded. At the same time, the transistors Q_a and Q_c are turned on in response to the pulses ϕ_{t1} and ϕ_{t2} to clear the carriers from the capacitors C_{11} to C_{n1} and C_{12} to C_{n2} , respectively.

[0261] For a time interval T_{m2} , the transistors Q_a are kept on in response to the pulse ϕ_{t1} to supply the read pulse ϕ_r to the sensors B. Therefore, the sensor signals S from the sensors B are stored in the capacitors C_{11} to C_{n1} , respectively. These sensor signals include the drive noise components of the corresponding sensors.

[0262] For a time interval T_{m3} , the transistors Q_r are kept on in response to the pulse ϕ_{rh} to ground the emitters of the sensors B. The sensors B are refreshed in response to the refresh pulse ϕ_r . Upon completion of refreshing, the transistors Q_{rh} are turned off, and the transistors Q_c are turned on in response to the pulse ϕ_{t2} . During this period, the read pulse ϕ_r is applied to read out the signals S from the sensors B. Their drive noise components, i.e., the above-mentioned reference signals E_1 to E_n are respectively stored in the capacitors C_{12} to C_{n2} . Thereafter, the pulse ϕ_r falls to cause the sensors B to start charge accumulation.

[0263] The above operations are performed during a blanking period BLK, and the signals temporarily stored in the corresponding capacitors are sequentially read out onto the output line 501A.

[0264] The transistors T_1 , Q_{e1} , and Q_{f1} are turned on in response to the pulse ϕ_1 . The voltage V_{cc} is applied to the amplifier A1, and the amplifier A1 is rendered operative (other amplifier A2 to A $_n$ are rendered inoperative). The pulse ϕ_{a1} rises in synchronism with the pulse ϕ_1 and the transistor Q_{b1} is turned on through the ON transistor Q_{e1} . The sensor signal S1 stored in the capacitor C_{11} is amplified by the

amplifier A1, and the amplified signal appears on the output line 501A and is then held in an S/H circuit 12A in a difference processing circuit 1A.

[0265] Subsequently, the pulse ϕ_{b1} rises and then the transistor Qd1 is turned on through the transistor Qf1. The reference signal E1 stored in the capacitor C12 is amplified by the amplifier A1, and the amplified signal appears on the output line 501A and then held by an S/H circuit 13A.

[0266] It can be assumed that a potential of an input to the amplifier A1 can be reset to a reference potential for a period from the time when the sensor signal S1 is output from the capacitor C11 to the amplifier A1 and to the time when the reference signal E1 is output from the capacitor C12.

[0267] However, most of the input capacitance of the amplifier A1 is an overlap capacitance of the transistors. The input capacitance is sufficiently smaller than the capacitances of the capacitors C11 and C12, and the residual charge can be neglected. Steady pattern noise caused by variations in amplifier characteristics is typical when the image signal is small. In this case, the residual charge is further decreased.

[0268] From the above reasons, a means for resetting the input terminals of the amplifiers A1 to An is omitted. However, in an application wherein the residual charge cannot be neglected, a reset means must be connected to the inputs of the amplifiers A.

[0269] When the sensor and reference signals S1' and E1' are respectively held by the S/H circuits 12A and 13A, the above-mentioned difference processing is performed to cause the differential amplifier 14A to produce the sensor signal S1 as the output signal Vout free from the drive noise component and the noise component N1. Similarly, the sensor outputs S1 to Sn are sequentially output.

[0270] When all sensor signals are output, the next sensor signals corresponding to the incident light are stored in the sensors B. In the same manner as described above, sensor read access and refreshing are performed for the blanking period BLK. Charge accumulation of the sensors B and dot sequential operation of the sensor signal temporarily stored in the capacitors are simultaneously performed.

[0271] When the clamp circuit shown in Fig. 19 is used in the difference processing circuit 1A, the capacitor C12 for charging the reference signal E1 and then the capacitor C11 for charging the sensor signal S1 must be discharged. This applies to the signal readout operations of the sensor signals S2 to Sn.

[0272] Fig. 21 shows a schematic arrangement of an image pickup system using any one of the image pickup apparatuses of the embodiments as an image pickup device.

[0273] Referring to Fig. 21, an image pickup device 601A comprises an image pickup apparatus of any one of the above embodiments. The gain or the like of the output signal Vout is controlled by a signal processing circuit 602A, and the resultant signal is output as an image signal.

[0274] Various pulses ϕ for driving the image pickup device 601A are supplied from a driver 603A. The driver 603A is operated under the control of a control unit 604A. The control unit 604A controls the gain or the like of the signal processing circuit 602A on the basis of the output from the image pickup device 601A and also controls an exposure control unit 605A to adjust an amount of light incident on the image pickup device 301A.

[0275] As described above, in the solid state image pickup apparatus according to the above embodiments, a difference between the selected sensor signal and the selected reference signal is calculated to obtain an output signal free from the noise components.

Therefore, the variations in readout signal depending on the potential variations of the input/output characteristics of the selector can be corrected. The steady pattern noise caused by the variations in amplifier characteristics can be eliminated.

[0276] A photoelectric transducer element used in Figs. 16A to 21 will be described as a supplementary explanation of Figs. 15C to 15E.

[0277] Fig. 22A is a schematic sectional view of a photoelectric transducer cell described in Japanese Patent Laid-Open Gazettes No. 12759/1985 to 12765/1985, and Fig. 22B is an equivalent circuit diagram of the cell.

[0278] Referring to Figs. 22A and 22B, photoelectric transducer cells are formed on an n^+ -type silicon substrate 701A and each photoelectric transducer cell is electrically insulated from adjacent photoelectric transducer cells by an element isolation region 702A made of SiO_2 , SiH_3N_4 , or polysilicon.

[0279] Each photoelectric transducer cell has the following structure.

[0280] A p-type region 704A doped with a p-type impurity is formed on an n -type region 703A formed by an epitaxial technique and having a low impurity concentration. An n^+ -type region 705A is formed in the p-type region 704A by impurity diffusion or ion implantation. The p-type region 704A and the n^+ -type region 705A respectively serve as the base and emitter of a bipolar transistor.

[0281] An oxide film 706A is formed on the n -type region 703A, and a capacitor electrode 707A having a predetermined area is formed on the oxide film 706A. The capacitor electrode 707A opposes the p-type region 704A through the oxide film 706A and controls a potential of the p-type region 704A floating upon application of a pulse voltage to the capacitor electrode 707A.

[0282] In addition, an emitter electrode 708A is connected to the n^+ -type region 705A, an n^+ -type region 711A having a high impurity concentration is formed on the lower surface of the substrate 701A, and a collector electrode 712A is formed to apply a potential to the collector of the bipolar transistor.

[0283] The basic operation of the above arrangement will be described. Assume that the p-type region 704A serving as the base of the bipolar transistor is set at a negative potential. Light 713A is incident from the side of the p-type region 704A. Holes in the electron-hole pairs generated upon radiation are accumulated in the p-type region 714A and the potential at the p-type region 714A is increased by the accumulated holes in the positive direction (charge accumulation).

[0284] Subsequently, a positive read voltage is applied to the capacitor electrode 707A, and a read signal corresponding to a change in base potential during charge accumulation is output from the floating emitter electrode 708A (read operation). It should be noted that the amount of accumulated charge is rarely reduced in the p-type region 704A serving as the base of the bipolar transistor, so that read access can be repeated.

[0285] In order to remove the holes from the p-type region 704A, the emitter electrode 708A is grounded, and a refresh pulse of a positive voltage is applied to the capacitor electrode 708A. Upon application of the refresh pulse, the p-type region 704A is forward-biased with respect to the n^+ -type region 705A, thereby removing the holes. When the refresh pulse falls, the p-type region 704A restores the initial state of the negative potential (refresh operation). Charge accumulation, read access, and refreshing are repeated as described above.

[0286] In order to restore the initial potential state of the p-type region 704A by refreshing, a refresh pulse having a sufficient pulse width is required. To the contrary, the refresh pulse width must be shortened to achieve high-speed operation. In this case, when the refresh pulse width is short, satisfactory refreshing cannot be performed. Unnecessary components such as a dark signal and drive noise are added to the after image.

[0287] Fig. 23 is a graph showing the relationship between a refresh pulse width t applied to the photoelectric transducer cell and the photoelectric transducer cell output.

[0288] Referring to Fig. 23, an output at $t = 0$ is a read signal after charge accumulation and represents a read signal after charge accumulation and represents a read signal having a level corresponding to the intensity of the incident light.

[0289] The output level of such a photoelectric transducer is reduced by refreshing. However, the rate of change in output level and the level of the residual image upon refreshing vary depending on the intensity of the incident light.

[0290] When identical refreshing is performed, the levels of the residual signals are not constant. When the intensity of the incident light is high, the level of the residual signal is high. In other words, the after image is typically formed.

[0291] The residual signal level of high-intensity incident light is higher than that of low-intensity incident light but is greatly lowered as compared with the initial read signal level. The ratio of the unnecessary components contained in the read signal is substantially low. On the contrary, the residual signal level of the low-intensity incident light is low. A decrease in the residual signal level is small as compared with the initial read signal level. Therefore, the ratio of the unnecessary components included in the read signal is high.

[0292] Even in the photoelectric transducer cell having the above characteristics, by subtracting the residual signal obtained upon refreshing from the initial read signal, the above-mentioned specific after image components as well as the unnecessary components such as a dark signal and drive noise can be simultaneously removed.

[0293] Another embodiment of the present invention will be described below.

[0294] Fig. 24 is a circuit diagram for explaining the basic arrangement of an image pickup element according to another embodiment of the present invention.

[0295] Referring to Fig. 24, an emitter electrode 708A of a photoelectric transducer cell S is connected to a vertical line VL and is grounded through a transistor Qr. The vertical line VL is connected to storage capacitors Ct1 and Ct2 through corresponding transistors Qt1 and Qt2. The capacitors Ct1 and Ct2 are connected to output lines 721A and 722A through transistors Qs1 and Qs2, respectively. The output lines 721A and 722A are connected to the input terminals of a differential amplifier 721A, respectively.

[0296] A pulse ϕ from a scanning circuit SH is applied to the gate electrodes of the transistors Qs1 and Qs2. Pulses ϕ_{t1} and ϕ_{t2} are applied to the gate electrodes of the transistors Qt1 and Qt2, respectively. A pulse ϕ_{rh} is applied to the gate electrode of the transistor Qr. A read or refresh pulse ϕ_r is applied to a capacitor electrode 707A of the photoelectric transducer cell S.

[0297] The operation of the above arrangement will be described below.

[0298] Fig. 25 is a timing chart for explaining the operation of the circuit shown in Fig. 24.

[0299] The transistors Qt1, Qt2, and Qr are turned on in response to the pulses ϕ_{t1} , ϕ_{t2} , and ϕ_{rh} , respectively, to clear the capacitors Ct1 and Ct2 (time interval T1).

[0300] Subsequently, the pulse ϕ_r is supplied to the capacitor electrode 707A while the transistor Qt1 is kept on. The read signal from the photoelectric transducer cell S is stored in the capacitor Ct1 (time interval T2).

[0301] The transistor Qt1 is turned off while the pulse ϕ_r is kept applied to the capacitor electrode 707A. The transistor Qr is turned on in response to the pulse ϕ_{rh} . The photoelectric transducer cell S is refreshed in response to the pulse ϕ_{rh} (time interval T3).

[0302] Upon completion of refreshing, the transistor Qt2 is turned on in response to the pulse ϕ_{t2} while the pulse ϕ_r is kept applied to the capacitor electrode 707A. The residual signal of the photoelectric cell S is stored in the capacitor Ct2 (time interval T4).

[0303] When the read and residual signals are stored in the capacitors Ct1 and Ct2, respectively, the transistors Qs1 and Qs2 are turned on in response to the pulse ϕ . The read and residual signals are input to the differential amplifier 723A through the corresponding output lines 721A and 722A. A signal Vout proportional to the difference between the read and the residual signals is output from the differential amplifier 723A (time interval T5).

[0304] As described above, the signal Vout is a signal free from the after image component and the unnecessary components such as a dark signal and drive noise and accurately corresponds to the intensity of the incident light. In particular, unnecessary component removal on the low-intensity side is effective, and an S/N ratio can be greatly increased.

[0305] Fig. 26 is a circuit diagram of an image pickup system of this embodiment. The circuit in Fig. 26 has n circuits of Fig. 24.

[0306] Referring to Fig. 26, the emitter electrodes 708A of photoelectric transducer cells S1 to Sn are respectively connected to vertical lines VL1 to VLn. The same circuits as in Fig. 24 are connected to the vertical lines. The gate electrodes of the transistors Qr are commonly connected, and the pulse ϕ_{rh} is applied thereto. The gate electrodes of the transistors Qt1 and the gate electrodes of the transistor Qt2 are also commonly connected, and the pulses ϕ_{t1} and ϕ_{t2} are supplied to the common gate electrodes, respectively.

[0307] The gate electrodes of the transistors Qs1 and Qs2 corresponding to the photoelectric transducer cells S1 to Sn are connected to the parallel output terminals of the scanning circuit SH and receive the pulses ϕ_1 to ϕ_n , respectively. The transistors Qs1 are commonly connected to the output line 721A and the transistors Qs2 are commonly connected to the output line 722A. These output lines are grounded through corresponding transistors 103A. A reset pulse ϕ_{hrs} is supplied to the gate electrodes of the transistors 103A.

[0308] A mode of operation of the arrangement described above will be briefly described with reference to Fig. 27A.

[0309] Fig. 27 is a timing chart for explaining the operation of the above arrangement.

[0310] As already described above, the capacitors Ct1 and Ct2 corresponding to each photoelectric transducer cell are cleared during the time interval T1. During the time interval T2, the read signal from each photoelectric transducer cell is stored in the corresponding capacitor Ct1. During the time interval T3, each photoelectric transducer cell is refreshed. During the time interval T4, the residual signal of each refreshed photoelectric transducer cell is stored in the corresponding capacitor Ct2.

[0311] After the read and residual signals of each photoelectric transducer cell are accumulated in the manner described above, the pulse ϕ_1 from the scanning circuit SH is supplied to the gate electrodes of the transistors Qs1 and Qs2. The read and residual signals stored in the capacitors Ct1 and Ct2 of the photoelectric transducer cell S1 are read out and appear on the output lines 721A and 722A. A difference between these signals is calculated by the differential amplifier 723A, thereby removing unnecessary components and hence obtaining the output signal Vout.

[0312] When a signal is output from the photoelectric transducer cell S1, the transistor 103A is turned on in response to the pulse ϕ_{hrs} , and the charges left on the output lines 721A and 722A are removed.

[0313] In the same manner as described above, the read and residual signals of the photoelectric transducer cells S2 to Sn are output from the capacitors Ct1 and Ct2 and appear on the output lines 721A and 722A and are subjected to subtractions by the differential amplifier 723A, thereby sequentially outputting signals Vout.

[0314] Fig. 27B shows another mode of operation of the above arrangement.

[0315] During a time interval T_s , the base electrodes of the cells S are reverse-biased to perform charge accumulation. Upon completion of charge accumulation, unnecessary charges on the vertical transfer line VL and the storage capacitor Ct1 are removed before the photoelectric transducer signals are transferred to the storage capacitor Ct1 within a time interval T_{vc} .

[0316] Refreshing is performed again during a time interval T_{c1} , and drive noise is transferred to the storage capacitor Ct2 during a time interval T_{t2} . Thereafter, the cell S is refreshed during a time interval T_{c2} , and the next charge accumulation cycle is initiated. The photoelectric transducer signal and drive noise which are stored in the

storage capacitors Ct1 and Ct2 are output onto horizontal signal lines 721A and 722A, respectively.

[0317] In the above embodiment, the sensor shown in Figs. 22A and 22B is exemplified. However, the present invention is not limited to any specific scheme of the photosensor.

[0318] The present invention can be applied to a color image pickup apparatus of a scheme for processing a plurality of horizontal line signals.

[0319] Fig. 28 is a circuit diagram of a third embodiment of the present invention, and Fig. 29 is a detailed circuit diagram of a readout circuit Ri in this embodiment. This embodiment exemplifies a scheme for processing a signal of two horizontal lines. This can apply to any scheme for processing a signal of three or more horizontal lines.

[0320] Referring to Fig. 28, photosensors S are arranged in an m x n area. Mosaic R, G, and B filters are arranged on the sensor surface.

[0321] Column photosensor outputs are respectively output to the readout circuits R1 to Rn through vertical lines VL1 to VLn.

[0322] Referring to Fig. 29, in any readout circuit Ri ($i = 1, 2, \dots, n$), the vertical lines VLi are connected to storage capacitors Ct1 to Ct4 through transistors Qt1 to Qt4, and the capacitors Ct1 to Ct4 are connected to output lines 801A to 804A through transistors Qs1 to Qs4, respectively. Since the scheme for processing a signal of two horizontal lines is used, two capacitors for storing the read signals and two other capacitors for storing residual signals are formed.

[0323] The gate electrodes of the transistors Qt1 to Qt4 are commonly connected through corresponding readout circuits R1 to R4. Pulses $\phi t1$ to $\phi t4$ are supplied to the gate circuits of the transistors Qt1 to Qt4.

[0324] A pulse ϕ_i from a horizontal scanning circuit SH is supplied to the transistors Qs1 to Qs4 of the readout circuit Ri. The transistors Qs1 to Qs4 are simultaneously turned on/off.

[0325] The output lines 801A and 802A are connected to the input terminals of a differential amplifier 805A, and the output lines 803A and 804A are connected to the input terminals of a differential amplifier 806A. Signals OUT1 and OUT2 are output from the differential amplifiers 805A and 806A, respectively.

[0326] Two lines per field are selected by a vertical scanning circuit 807A and an interlace circuit 808A (Fig. 28). Pairs of two horizontal scanning lines in units of fields are selected in response to pulses Vr1 and Vr2.

[0327] The operation of the above circuit will be described with reference to Fig. 30.

[0328] Fig. 30 is a timing chart for explaining the operation of the above circuit.

[0329] Each photosensor read signal and its residual signal for two horizontal lines are read out during a horizontal blanking (HBLK) period and are stored in the storage capacitors in the readout circuits R1 to Rn. Transfer of one of the two horizontal lines is performed during a time interval Ta in response to the pulse Vr1. Transfer of the remaining horizontal line is performed during a time interval Tb in response to the pulse Vr2.

[0330] The transfer operations are substantially the same as those in Fig. 26. However, since transfer is performed during the HBLK period, the transfer time can be shortened as compared with a scheme for processing a signal of one horizontal line. Clearing of the residual signal storage capacitor and its charge accumulation are performed during substantially equal time intervals T3' and T3". Smear generated during signal transfer is

proportional to the transfer time. In this sense, T_2 (T_2') and T_3' (T_3'') are shortened to suppress the smearing phenomenon.

[0331] The capacitors C_{t1} and C_{t2} are cleared within a time interval T_1 in the time interval T_a . During a time interval T_2 , a pulse ϕ_{r1} is supplied to the first horizontal line in response to the pulse V_{r1} , and read signals of the photosensors on the first horizontal line are stored in the capacitors C_{t1} in the readout circuits R_1 to R_n . Subsequently, during a time interval T_3' , the photosensors of the first horizontal line are refreshed, and the residual signals upon completion of refreshing are stored in the capacitors C_{t2} .

[0332] During the next time interval T_b , the same transfer as in the first horizontal line is performed for the second horizontal line in response to the pulse ϕ_{r2} generated in response to the pulse V_{r2} . The read and residual signal of each photosensor for the second horizontal line are respectively stored in the capacitors C_{t3} and C_{t4} .

[0333] When the read and residual signals of the first and second horizontal lines are stored in the capacitors C_{t1} to C_{t4} of the readout circuits R_1 to R_n , the pulses ϕ_1 to ϕ_n from the horizontal scanning circuit SH are sequentially output to the readout circuits R_1 to R_n , so that an R- and G-dot sequential signal OUT_1 and a G- and B-dot sequential signal OUT_2 which are free from the unnecessary components are output from the differential amplifiers 805A and 806A, respectively. It should be noted that the signal OUT_1 is a G- and B-dot sequential signal and the signal OUT_2 is an R- and G-dot sequential signal in the next field.

[0334] Fig. 31 is a schematic block diagram of an image pickup system using the solid state image pickup apparatus as an image pickup device.

[0335] An image pickup device 901A comprises an image pickup apparatus shown in Figs. 28 and 29. The output signals OUT1 and OUT2 from the image pickup device 901A are processed by an image processing circuit 903A through a sample/hold (S/H) circuit 902A to produce a standard television signal such as an NTSC signal.

[0336] Pulses for driving the image pickup device 901A are supplied from a driver 904A. The driver 904A is controlled by a control unit 905A. The control unit 905A also controls an exposure control unit 906A to determine an intensity of light incident on the image pickup device 801A.

[0337] According to the image pickup apparatus according to this further embodiment of the present invention, as described above, the residual signal is subtracted from the read signal of the photoelectric transducer cell upon its refreshing to remove the unnecessary components (e.g., a dark signal and drive noise) of the photoelectric transducer element, thereby obtaining a video signal having a high S/N ratio. As a result, a low-cost, compact image pickup apparatus can be manufactured.

[0338] Fig. 32 is a schematic view of an area sensor for simultaneously reading out signals of two horizontal lines. This circuit includes switching transistors Tr11 to Tr22, bipolar transistors B-Tr10 and B-Tr20, and capacitors Cox10 and Cox20. In this sensor, a photoelectric transducer signal and driver noise of the bipolar transistor B-Tr10 are respectively stored in the capacitors Ct1 and Ct2. A photoelectric transducer signal and drive noise of the bipolar transistor B-Tr20 are respectively stored in the capacitors Ct3 and Ct4. When these signals are to be read out, the photoelectric transducer signals are simultaneously and independently read out onto horizontal signal lines S2 and S3, and drive noise components are simultaneously output onto the horizontal signal line S1. Therefore, the drive noise components are output as a sum

signal. R and G filters in an order of R, G, R, G, . . . are formed on photoelectric transducer elements of the even-numbered rows, and G and B filters in an order of G, B, G, B, . . . are arranged on photoelectric transducer elements of the odd-numbered rows.

[0339] Fig. 33 shows an image pickup system using the area sensor shown in Fig. 32.

[0340] The image pickup system includes an inversion amplifier 60A, an adder 70A, a color separation circuit 80A, a color image signal processing system 90A, an area sensor 10'A, a driver 20'A, and a clock generator 30'A.

[0341] Photoelectric transducer signals S2 and S3 read out from the area sensor 10'A are input to the adder 70A and are averaged, thereby obtaining a signal in the form of $R + 2G + B$. The drive noise is inverted by the inversion amplifier 60A, and the inverted signal is input to the adder 70A. The adder 70A subtracts the drive noise from the photoelectric transducer signal, thereby producing a luminance signal Y consisting of only an information signal.

[0342] The color separation circuit 80A receives the photoelectric transducer signals S1 and S2 and separates them into chrominance signals R, G, and B. The resultant signals Y, R, G, and B are processed by the color image signal processing system 90A. The processing system 90A generates a standard television signal such as an NTSC signal.

[0343] In the above embodiment, the scheme for simultaneously reading out signals of two horizontal lines is used. However, the present invention is applicable to a scheme for simultaneously reading out signals of three horizontal signals.

[0344] The storage capacitors can be omitted if the image pickup apparatus includes a shutter.

[0345] A subtracter for removing the drive noise may be connected to the output terminal within the apparatus.

[0346] In the above embodiment, the drive noise can be output independently of the photoelectric transducer signal, so that an external large-capacity memory need not be arranged.

[0347] In the horizontal line readout scheme, since the noise components can be added and its sum can be output, the number of horizontal signal lines can be reduced.

Therefore, a multi-horizontal line readout scheme can be easily achieved.

[0348] Fig. 34 shows still another embodiment of the present invention. In this embodiment, the differential amplifier 723A in Fig. 24 is replaced with a clamp circuit. The same reference numerals as in Figs. 15 to 33 denote the same parts in Fig. 34.

[0349] Fig. 35 is a timing chart for explaining the operation of the circuit shown in Fig. 34.

[0350] Cells S are reverse-biased to perform charge accumulation during a time interval T_s . Upon completion of charge accumulation, the unnecessary charges on the vertical transfer lines VL and in the storage capacitors Ct1 are removed prior to transfer of photoelectric transducer signals within a time interval T_{vc} . The photoelectric transducer signal is transferred to a corresponding storage capacitor Ct1 during the time interval T_{t1} .

[0351] Refreshing is performed during a time interval T_{c1} , and drive noise is transferred to the storage capacitor Ct2 during a time interval T_{t2} . Thereafter the cells S are refreshed during a time interval of T_{c2} , and the next charge accumulation cycle is initiated. The photoelectric transducer signals and the drive noise are independently obtained. The signals stored in the storage capacitors Ct1 and Ct2 are dot-sequentially

transferred on a single signal line S in response to drive pulses ϕ_{s1} and ϕ_{s2} . This operation occurs during time intervals TR1 and TR2. A drive pulse ϕ_{hrs} is used to reset the signal line to the reference potential. The signal obtained by the above-mentioned read operation represents a waveform of an output V_{out} . The drive noise and the photoelectric transducer signal are represented by W and S', respectively.

[0352] The dot sequential signal S is input to a clamp circuit 1A, and only the drive noise N is clamped in accordance with a drive pulse ϕ_{s2} . As a result, the drive noise N is eliminated, and a true information signal indicated by a hatched portion in Fig. 35 can be obtained.

[0353] Fig. 36 is a schematic circuit diagram of an area sensor constituted by the photoelectric transducer elements shown in Fig. 34. Referring to Fig. 36, the area sensor includes a vertical shift register V-SR, a horizontal shift register H-SR, and S_{mn} , base accumulation type transistors arranged in an $m \times n$ matrix. The operation of the area sensor is basically the same as that of the photoelectric transducer element shown in Fig. 34, except that the area sensor performs horizontal scanning and vertical scanning, and a detailed description thereof will be omitted. Clamping of the read signal, which is the characteristic feature of this embodiment shown in Fig. 36, will be described in detail.

[0354] A schematic waveform of the read signal is shown in Fig. 37. A signal S' appears on a read signal line S, and a pulse ϕ_{s2} is a drive pulse. Referring to Fig. 37, drive noise and the photoelectric signal of a cell S11 correspond to N1 and S1, respectively. A cell S12 outputs signals N2 and S2, a cell S13 outputs signals N3 and S3, a cell S14 outputs signals N4 and S4, The drive noise component of the dot sequential signal is clamped in response to the drive pulse ϕ_{s2} . As a result, the drive noise is removed, and only the true information signal can be obtained.

[0355] The above embodiment exemplifies a scheme for reading out a signal of one horizontal line. However, this embodiment may be applied to a scheme for reading out a signal of one horizontal line in a time-divisional manner or a scheme for simultaneously reading signals of a plurality of horizontal lines, as shown in Fig. 28.

[0356] The base accumulation type transistor is exemplified as the photoelectric transducer element. However, a MOS or SIT image pickup device may be used as the photoelectric transducer element.

[0357] In the above embodiment, the drive noise and the photoelectric transducer signal are converted into a dot sequential signal, and clamping can be easily performed, thereby easily removing the drive noise.